

Product Disposal

Please dispose of this product thoughtfully once it has passed its useful life. At the end of their working life, do not throw the appliance out with your household rubbish. Electrical and electronic products contain substances that can have a detrimental effect on the environment and human health if disposed of inappropriately. Observe any local regulations regarding the disposal of electrical consumer goods and dispose of it appropriately for recycling. Contact your local authorities for advice on recycling facilities in your area.

Martec Australia Pty Ltd
Email: sales@martecld.com.au
Contact Phone: 02 8778 7500
Contact Fax: 02 8778 7555

Company Address:
6 Austool Place
Ingleburn NSW 1890

Opening Hours:
Monday to Friday
Warehouse hours: 7.30am – 3.30pm
Office hours: 8.00am – 5.00pm EST

WWW.MARTECAUSTRALIA.COM.AU

(For Warranty Conditions please refer to the Martec Warranty Terms and Conditions)

https://www.martecaustralia.com.au/wp-content/uploads/2023/05/Warranty-Statement_Cooling.pdf

BANDIT

BANDIT TRICOLOUR LED SPOTLIGHT Instruction Manual



MLXB3451M



MLXB3452M



NOTE : This product must be installed by a licensed electrician .

NOTE : For best performance install at a height between 1.8 and 2.5 metres .

Installation

1 Ensure the Mains Supply is switched OFF.

2 Unscrewing the front screw.

3 Remove the mounting base "B" from the light body "A".

4 1. Mark fixing hole positions. Locate wall plugs into drilled holes. 2. Fasten the backing

5 Put the silicone plug into the mounting holes

6 Connect the Live (L), Neutral (N), according to the marking on the terminal block .

7 Selete desired CCT (WW-NW-CW)

8 Refit the light body "A" to the mounting base "B", securing it in place. Tighten them firmly to maintain IP rating

9 1. Loose the screw in knuckle and angle the light head into desired direction, then re-tighten the screw firmly . 2. Recontact the mains supply, Turn on the light .

Rotation of lamp head

The lamp head can be rotated up and down 120°

The lamp head can be rotated left and right 340°

The product is energy - saving automatic sensor lamp , adopting integrated circuit and precise detecting components .It gathers automatism ,convenience ,safety,saving-energy and practical function . Its performance is stable . It can identify day and night .The lamp can turn on when one entes detection field and can turn off automatically when one leaves detection field.

Part list

Single Head

MLXB3451M

Double Head

MLXB3452M

Back View

Accessories

1 × silicone plugs

1 × silicone plugs

2 × wall plugs

2 × M4 screw

Specification

Item No.	MLXB3451M	MLXB3452M
Product Name	BANDIT Tricolour Single Head LED Spotlight	BANDIT Tricolour Double Head LED Spotlight
Wattage	12W	24W
Input Voltage	220-240VAC	220-240VAC
Lumen	1050lm / 1100lm / 1100lm	2100lm / 2200lm / 2200lm
CCT	3000K-4000K-5000K	3000K-4000K-5000K
IP Rating	IP54	IP54
Beam angle	90°	90°
CRI	>80	>80
LED	COB LED	COB LED
Material	Plastic (ABS & PC)	Plastic (ABS & PC)